ARTISAT 36" JACK-TYPE 8 SHAFTS BACK HINGE TREADLES 1009-3628



On receiving the loom, unpack and lay out the loom components

Do NOT discard any packing material until all parts are inventoried.

Check the parts received against the parts list on pages #2 to #7 of the assembly instructions. Report any discrepancies to Leclerc immediately.

To assemble this loom, a minimum of 2 are needed but 3 persons are favorable.






1573 Savoie C. P. 4 Plessisville, Qc. G6L 2Y6

TEL: 819-362-7207 FAX: 819-362-2045


leclerc@leclerclooms.com www.leclerclooms.com

Dec. 02 1999 leclerc\inst\artisat\8sbhtt.frp


PARTS LIST (8s)




PARTS LIST (8s)



PARTS LIST



10 treadles with rocker piece




1 Treadle Separator 40" long



10 Treadle springs with Loop cord 6" (9½" with spring)

PARTS LIST (8s)



8 SHAFT (harness) FRAMES

1 REED

0

2 LEASE STICKS

1 BEAM STICKS

3 WARP RODS

1000 HEDDLES

1 HEDDLE AND REED HOOK 8 5/8" long 6140-9000

1 Multi bits SCREWDRIVER




1 Adjustment wrench



10 TREADLE HOOK 9½ " LONG




60 TREADLE CORDS 61/2"




1 CRANK FOR BACK BEAM

PARTS LIST (8s)

1 - 7/16 X 3½" (12 mm 90 mm)



Carriage Bolts



- 2 1/4 X 31/4" (6 mm x 80 mm)
- 2 1/4" X 3" (6 mm x 75 mm)
- 2 1/4" X 13/4" (6 mm x 45 mm)
- 4 5/16 X 2½" (8 mm x 65 mm)
- 2 1/4" x 21/4" (stab. post)

Nuts



- 2 1/4" (6 mm)
- 2 5/16" (8 mm)

Washers

- 1 9/16 cloth beam
- 2 9/16" treadle set
- 4 5/16" (8 mm)

Flat head screw



4 - #12 X 1½" (38 mm)



2 eye screws




Round head screw

- 6 #14 X 2" (50 mm)
- 2 #8, 11/4" (treadles separator)
- 8 #12, 1½" (jack box)
- 6 #8, 1" (stab. post hinges)

Wing nuts


- 6 1/4" (6 mm)
- 2 5/16" (8 mm)

10 Loop cord 16" ($13\frac{1}{2}$ " cc black mark) long for treadle rocker






WARP AND
WEAVE
***CORPT LECURE**





Tacks for canvas PAGE 6




1 VHS Video cassette Showing all stage of the installation

ASSEMBLY








Using two 2" (50 mm) round-headed screws no. 14, affix one of the two breast beams to the top of the front posts B and B`

The rounded angle must be towards the outside of the loom.


PAGE 8



ATTACHING THE NEW STABILIZING ASSEMBLY TO THE LOOM


Install the new rear Stabilizing assembly (A) to the Warp Beam Posts using 6 Round Head Screws #8 - 1"

Anchor the hook (B) to the stabilizing post using 2 carriage bolts $2\frac{1}{4}$ " x $\frac{1}{4}$ " and 2 wing nuts $\frac{1}{4}$ " (outside of the loom)



TREADLE SEPARATOR


Affix the Treadle Separator Board on top of the back of the side base and secure using 2 #8, 11/4" Round Head Screws.



TREADLE SET ASSEMBLY

Assemble the treadle set (in or out of the loom) as shown in picture using:

- 1 treadle rod 28"
- 10 treadles
- 9 wood spacers
- 2 treadle blocs
- 1 x 1/4" washers
- 2 push nut 7/16"




2 washers always between treadle and treadle bloc.

Affix treadle set to the treadle cross-member

using: 2 carriage bolts 1/4" x 31/2"

2 washers 1/4" (under cross member)

2 Wing nuts 1/4"



NOTE: The 10 screws goes in front bottom of the loom.

The eyescrews goes in the back bottom of the loom.


Install the heddles in the shaft frames. (see "WARP AND WEAVE" on page 10)


Remove the saran wrap of the jack box.

Slide shaft frames T between dividers Q.

The shaft frames must rest on the plastic supports U of the jacks

NOTE: Some shafts may be tight between castle frame untill the castle top is fix.






Castle cover


Complete the assembly with securing the Castle cover with 4 #12 1½" flat screws. Make sure to screw in the pre-drill holes of the castle.






Using the carriage bolts, steel washers and square nuts, attach the batten sley A (with shuttle race) to the batten swords B.


Then affix the batten handtree C to the batten swords B.






TREADLE SPRINGS

Insert the Spring Rod and Springs in the Screw Eyes below the Jack Board aligning one spring above each treadle. (see diagram)







Unhook brake treadle cord C from the brake realease treadle.


Hold circular wire brake shoe D up slightly to the rear of the loom.


Insert one end of the warp beam (which has only a metal post) into the left-hand side back post.



Do not unroll the brake shoe (brake circle), just slide the warp beam into it








Attach the end of circular brake shoe D (wire brake circle) to the hook of spring F

Then attach cord C to the hook of brake treadle G passing cord under pulley A

See "Warp and Weave book (friction brake section page 87)

FIRST TREADLE TIE-UP

Select any treadle and tie the Lams to Treadles using the 6 ½" cords supply with the loom. Take the treading hook to help passing the cord through each hole of the lam.




TREADLE HOOK AND ROCKER LOOP CORD

Slide the Treadle Hook thru the Screw Eyes and Cord Loops. Before the last Screw Eye, insert the Hook thru the Treadle Spring and secure. In the Treadle rest position(up) there should be no or very little tension on the Spring. However slack on those cords is not desirable. When all treadles are tie-up, they should be at same height.

Rocker loop cord


Install the Treadle Rocker Loop Cord on the Anchors(Screw Heads) using the marked points at the Anchor.(see diagram)





11) FIRST SHED


When you depress the Treadle, the Rocker Loop Cord raises the front Rocker setting the Shafts at the collevel. (see diagram)




Loop cord screw


Treadle

12) VIEW FROM THE BACK OF THE LOOM SHOWING THE TREADLE AT REST POSITION AND DEPRESS






BEAMING




Thread the 10 yard (9 m) cord trought the middle hole of beam stick A. Then pass the two ends (equal in lenght) of this cord trought the niddle holes of the warp beam.




Continue threading the cord trought the warp beam and beam stick A. Knot the cord at each end of the beam stick.

Adjust the cord so it is equally divided and keeps the beam stick straight. This will reduce warp wastage.



Cut the 5-yard (4.5 m) cord in half. One half of this cord laces beam stick A to warp rod B Insert a metal rod into the apron of the cloth beam. Use the other half of the cord to lace this rod to the third metal rod.



ADJUSTING THE SHED WITH A BACK HINGE TREADLES LOOM.

The key to a wide clean Shed is the proper adjustment of the Rocker Loop Cord. Once you have completed the hookup of Cords and Springs, start at one end of the Treadle Set and depress each Treadle one at a time noting the position of the bottom Shed. Adjust each Shed by shortening or lengthening the Loop Cord.

When properly adjusted, the bottom Shed of each Treadle should just kiss the Race Plate and the top Shed uniform across the width of the Loom.(see diagrams for examples)

Picture #1 shows an uneven Shed caused by Rocker Loop Cords being out of adjustment.

Picture #2 shows properly adjusted Rocker Loop Cords with the bottom Shed just kissing the Race Plate and the Top Shed uniformly even across the width.

It is very important to maintain a reasonable amount of tension on the Warp when making adjustments and while weaving in order to keep a wide, clean Shed.

The design of the system provides a greater lifting force on the Shafts with considerably less Leg pressure required to depress the Treadles. With a few Picks on each new project, the Weaver will find the correct Warp tension required to produce the desired PPI(Picks per Inch) in the Cloth, while maintaining a wide, clean Shed.

We at Leclerc encourage Weaver feedback on this and all our products. Please send your comments to Leclerc Loom Co.

HAPPY WEAVING

We at Leclerc encourage Weaver feedback on this and all our products. Please send your comments to Leclerc Loom Co.



